

# WISI DXC 0932

FLEXSWITCH multiswitch 9 in 32, cascade



## Description

The DXC 0932 cascadable multiswitch is equipped with 8 satellite IF polarization input and 1 terrestrial input. They all could be forwarded to the corresponding trunk outputs and to other possible connected multiswitches and they could be switched to up to 32 subscriber outputs. Any commercial available DVB-S/S2 set-top-boxes as well as any TVs with integrated satellite receiver can be connected to this outputs. More than that, terrestrial DVB-T/T2, DAB+ or FM signals can be additionally inserted over the corresponding input connector and can be distributed to all connected multiswitches in cascade or any reception devices. The multiswitch itself and any preconnected multiswitches or LNB can be supplied over the DC input connector by using one of the external power supplies DXP 1812 or DXP 1830, depending on the requested power.

## At a glance:

- Cascadable multiswitch for the distribution of 8 satellite polarisations and terrestrial signals
- Active terrestrial path to distribute DVB-T/T2, DAB and FM without an additional amplifier
- Integrated SAT amplifier for low insertion loss
- Pre-emphasis to compensate the cable loss at high frequencies
- High screening efficiency according to Class A
- Compact dimensions paired with installation friendly distance between the F-connectors
- Colour-coded inputs and outputs
- Compatible with all cascadable DXC 09xx

**Technical data**

<b>SAT-IF trunk</b>	
Inputs SAT	8 pcs.
Outputs SAT	8 pcs.
Frequency range-SAT	950...2150 MHz
Through loss SAT	7 dB
Isolation SAT -SAT	30 dB typ.
Return loss SAT	>10 dB

**Terrestrial trunk**

Inputs TERR	1 pcs.
Outputs TERR	1 pcs.
Frequency range TERR	47...862 MHz
Through loss TERR	5 dB
Isolation TERR - SAT	30 dB typ.
Return loss TERR	>10 dB

**Subscriber outputs**

Outputs	32 pcs.
Frequency range	47...2150 MHz
TERR type	Active
Insertion loss SAT	4...-1 dB
Insertion loss TERR	0 dB
Max. output level subscriber SAT	100 dB $\mu$ V (IMA3 @ 35dB)
Max. output level subscriber TERR	90 dB $\mu$ V (IMA3 @ 60 dB)
Return loss subscriber SAT	>10 dB
Return loss subscriber TERR	>10 dB
Control signal	13/18 V, 0/22 kHz, DiSeqC 1.0/2.0
Current consumption from receiver	max. 50 mA

**Connectors**

F-Female	50 pcs.
Impedance	75 $\Omega$
DC supply voltage	F-Female
Color code	VL = black; HL = green; VH = red; HH = yellow

**General data**

Operating voltage	15...20 V DC
Power consumption max.	<3.5 W
Screening factor	Class A, according to EN 50083-2
Operating temperature range	-20...55 °C
Weight	1.1 kg
Dimensions (width x height x depth)	300 x 175 x 60 mm

**Packaging data**

Sales unit	1 pcs.
Dimensions (WxHxD) sales unit	318 x 185 x 65 mm
Packaging volume sales unit	3.9 dm <sup>3</sup>
Gross weight sales unit	1.25 kg
EAN	4010056768843
Article number	76884
Customs tariff number	85437090